Initial configuration of a SAMSUNG tizen screen

The initial configuration is loaded automatically the first time the screen is started. However, this configuration wizard can be called up manually at any time using the remote control :

MENU > System > Configuration PS : if the configuration menu is greyed out, first change the source to PC and try again..

Etape 1 : power up

- Take the remote control.
- Turn on the screen, a welcome message appears. We recommend that you leave the language in English by selecting "Welcome".

lower or mute the sound to interrupt the welcome music, if necessary.



Etape 2 : orientation choice

Last update: 2020/06/22 en:configuration_initiale_des_ecrans_tizen https://documentation.zebrix.net/doku.php?id=en:configuration_initiale_des_ecrans_tizen&rev=1583764793 11:53

Choose the "Landscape" or "Portrait" orientation depending on the physical orientation of the screen. If you don't know which orientation will be used later, choose "Landscape".

<		1 2	3 4	5	>
	Display Or	ientation			
Se	lect the display's installation orie content will be displayed in Select to install the dis	ntation. The onscreen me the selected orientation. splay horizontally.	enu and		
	Landscape Portrait		~		

Etape 3 : desactivate auto power off

desactivate "auto power off" : select" off".



Etape 4 : Network configuration

If the question is asked, choose "Wired" for a cable connection, choose "Wireless" for a wifi connection. The wizard then starts a connectivity test.



If the connectivity test is successful, the following confirmation is displayed :



If you using static IP settings

If the screen has to be configured on a static ip, you can interrupt the test with the "STOP" button (or wait for the test to fail) and then use the "IP SETTINGS" button to specify the static IP settings.

Etape 5 : date and time settings

Set the date and time on the screen

<					~	~	3	4	5	>
		Set the Set current da	Cloc current t te using the	k Se ime and d numeric or u	t late firs p/down bi	t. uttons.			(
[Date					/,	/			
	Time						:			

Etape 6 : "URL Launcher" mode

Select the player type "URL Launcher".

<					Ň	/ .	/	~	4	5				\rangle
	Sele	ct the pl ^{Use yo}	PL ayer type ur own appl	ay v e that be ication ins	∕ia est meet tread of Ma	s your ne gicInfo.	eeds.							
	MagicIr	nfo								_		1		
	URL La	uncher	8				`	/				Ļ		
<									4	5				>
			Pl	ay v	via									
	Selec	ct the pl	ayer type	that be	est meet	s your ne	eeds.							
			Enter URL	to displa	y or down	load con	tent from					13/2	200	
	screen		screens		screene	ed	scree		SCI					screenplay
	û	1	2	Θ	4	5	6		8	9	0	<	×	Delete All
	#@!	q	s	e	(i)	t	у	U		0	р			
		a	S	\odot	f	g	h	j	k	ι	~	@	!	Done
		Z	×	С	v	b	n	m			?		-	
		\$	<u>ئې</u>		L	_		www.	.com		<		>	Cancel

Enter the URL of the zebrix server you were given using the virtual keyboard.

Usually the URL is :

For the USA http://screen.zebrix.us For Europe http://screen.zebrix.net

Attention, it is possible that you have to use another URL, please contact our support if needed.

Last update: 2020/06/22 en:configuration_initiale_des_ecrans_tizen https://documentation.zebrix.net/doku.php?id=en:configuration_initiale_des_ecrans_tizen&rev=1583764793 11:53

Etape 7 : Device Name

You can skip this step using the right directional arrow on the remote control.

	~ ~ ~ .	5	
Device	Name		
Set the device name for nging the device names makes it easier to	or your SMART Signage. identify each signage on a PC or mobile device.	Signage 1	
Device Name: [Signage] Samsun	g PMF Series		
Device Name: [Signage] Samsun User Input	ng PMF Series		
Device Name: [Signage] Samsun User Input [Signage] Display 1	ng PMF Series	Signage 2	
Device Name: [Signage] Samsun User Input [Signage] Display 1 [Signage] Display 2	Ig PMF Series	Signage 2	
Device Name: [Signage] Samsun User Input [Signage] Display 1 [Signage] Display 2 [Signage] Display 3	Ig PMF Series	Signage 2	

Etape 8 : The configuration is complete

The configuration is complete



Check the firmware version and, if necessary, update it.

Some firmware are too old and/or are known to have problems.

Here's how to check the firmware version used:

With the remote control : MENU > Support > Contact Samsung > The firmware version should be visible.

Please update the firmware to the recommended version using a USB stick using the following steps : Mise à jour du firmware d'un écran Samsung SSSP à l'aide d'une clé USB

Remote update with Zebrix CMS

If your monitor is properly connected to zebrix, you can use the remote update function from the "hardware tools".

Etape 9 : Start Zebrix application

With the remote control: HOME > URL Launcher



The zebrix application will be downloaded and start.



Etape 10 : Screen activation

If the configuration went well, and the internet access is functional, the following activation page is displayed (only if the screen has never been activated before).

🕟 zebrix

ID :	40:16:3B:	
Conç	gratulations your screen is connected!	
	Please activate it.	
	By email : activation@zebrix.net	

Please send an e-mail to activation@zebrix.net to request screen activation on your zebrix account. Our support can also be reached at +33 3 20 41 59 69.

As soon as the screen is activated, the following message will appear :



Etape 11 : Activate "Auto souce switching" function

In order to ensure that the screen starts the zebrix application under all circumstances (even after an electrical restart, voluntary or involuntary source change, application crash, etc.), we recommend

enabling the "Automatic source change" function.

The purpose of this function is to always ensure that the source of the display is automatically switched to a predefined primary source or, if no signal is present on that source, to a predefined secondary source. Since zebrix can only be set as the primary source, we can choose a primary source that will always be unused (HDMI1 for example) and set zebrix as a secondary source. The screen will then try to display HDMI1, but as this source has no signal, zebrix will be launched after a few seconds.

For activate this function:



MENU > System > General > Auto source switching

	Changement so	Basculez sur la source prédéfinie ou une	
	Changement source au	Activé	autre source lorsque le périphérique source
G	Récup. source princip.	Activé	principal est déconnecté.
	Source principale	HDMI1	
R	Source secondaire	MagicInfo S/Lanceme	
X			
[2]			

- Auto source switching : activé
- Recovery primary source : activé
- Primary source : HDMI1
- Secondary source: MagicInfo S / URL launcher (= zebrix)

From: https://documentation.zebrix.net/ - zebrix documentation

Permanent link: https://documentation.zebrix.net/doku.php?id=en:configuration_initiale_des_ecrans_tizen&rev=1583764793

Last update: 2020/06/22 11:53

