



## Screen already in use: factory reset recommended

- Press the settings button on the remote control (cogwheel icon)
- Go to **admin**
- Enter pin code (default: 000000)
- Reset to factory, **the screen will go blank ===== New screen or first start-up after reset to factory settings ===== - Select Quickstart / Normal Configuration. - Configuration of screen rotation language, input rotation activation, source: adapt if necessary (default settings can be kept as they are). - Date and time configuration required! - Done**



**DATE / TIME: It is very important to correctly configure at least the correct date**, otherwise the first connection to zebrix in HTTPS will be impossible (certificate verification requires a correct date)

===== Configuring zebrix on the screen ===== - Start the screen with the **power** button on the remote control - Press the **parameters** button on the remote control (cogwheel icon) - In the **EZ Setting** category, go to SI Server Setting - Select **SI Server Setting**. - Set **Fully Qualified domain name** to **ON**. - Enter the URL: <https://screen.zebrix.net> - Application Launch mode: **Local** - Application Type: **ZIP** - Local application Upgrade: **press Remote and confirm, this will launch the application download.** - **Exit using the cross at top right** - **Turn off the screen using the power button on the remote control** - **Turn the screen back on using the same button and wait.** - **A few seconds after restarting, a notification will be displayed confirming that the application has been downloaded/updated.** - **A few seconds later, the application starts automatically and the zebrix activation page appears.** - **After activation by the zebrix team, we recommend that you reboot the screen with the remote control one last time before using it.**

From:  
<https://documentation.zebrix.net/> - zebrix documentation



Permanent link:  
[https://documentation.zebrix.net/doku.php?id=en:connect\\_luckygoldstar\\_screen&rev=1707731241](https://documentation.zebrix.net/doku.php?id=en:connect_luckygoldstar_screen&rev=1707731241)

Last update: 2024/02/12 10:47