



Screen already in use: factory reset recommended

- Press the settings button on the remote control (cogwheel icon)
- Go to **admin**
- Enter pin code (default: 000000)
- **Reset to factory**, the screen will go blank

New screen or first start-up after reset to factory settings

- Select **Quickstart / Normal Configuration**.
- Configuration of screen rotation language, input rotation activation, source: adapt if necessary (default settings can be kept as they are).
- **Date and time configuration required!**
- Done



DATE / TIME: It is very important to correctly configure at least the correct date, otherwise the first connection to zebrix in HTTPS will be impossible (certificate verification requires a correct date)

Configuring zebrix on the screen

- Start the screen with the **power** button on the remote control
- Press the **parameters** button on the remote control (cogwheel icon)
- In the **EZ Setting** category, go to SI Server Setting
- Select **SI Server Setting**.
- Set **Fully Qualified domain name** to **ON**.
- Enter the URL: <https://screen.zebrix.net>
- Application Launch mode: **Local**
- Application Type: **ZIP**
- **Local application Upgrade**: press **Remote** and confirm, this will launch the application download.
- Exit using the cross at top right
- Turn off the screen using the **power** button on the remote control
- Turn the screen back on using the same button and wait.
- A few seconds after restarting, a notification will be displayed confirming that the application has been downloaded/updated.
- A few seconds later, the application starts automatically and the zebrix activation page appears.

- After activation by the zebrix team, we recommend that you reboot the screen with the remote control one last time before using it.

From: <https://documentation.zebrix.net/> - **zebrix documentation**

Permanent link: https://documentation.zebrix.net/doku.php?id=en:connect_luckygoldstar_screen&rev=1707731416

Last update: **2024/02/12 10:50**

