

# Samsung SSSP USB Firmware Upgrade

## SSSP6 (Tizen 4) QBN/R, QMN/R, VMR QEN, OMN

- Download the current recommended firmware:



[http://www.zebrix.net/downloads/T-KTM2ELAKUC\\_2070\\_USB.zip](http://www.zebrix.net/downloads/T-KTM2ELAKUC_2070_USB.zip)

- Unzip the file
- Rename the obtained folder to **T-KTM2ELAKUC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## SSSP5 (Tizen) QBH, QMH, QHH, DBJ

- Download the current recommended firmware:



[http://www.zebrix.net/downloads/http://www.zebrix.net/downloads/QMH\\_QHH\\_QBH\\_QBH-N\\_DBJ\\_Main\\_WW\\_T-KTMLAKUC\\_2080.2\\_USB.zip](http://www.zebrix.net/downloads/http://www.zebrix.net/downloads/QMH_QHH_QBH_QBH-N_DBJ_Main_WW_T-KTMLAKUC_2080.2_USB.zip)

- Unzip the file
- Rename the obtained folder to **T-KTMLAKUC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## SSSP4 (Tizen 2.4) PMF, PHF

- Download the firmware :



[http://www.zebrix.net/downloads/PMF\\_PMF-BC\\_PHF\\_MLF\\_PHF-P\\_PMH\\_Main\\_WW\\_T-HKMLAKUC\\_2080.4\\_USB.zip](http://www.zebrix.net/downloads/PMF_PMF-BC_PHF_MLF_PHF-P_PMH_Main_WW_T-HKMLAKUC_2080.4_USB.zip)

- Unzip the file
- Rename the obtained folder to **T-HKMLAKUC**

- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## For SSSP v3 (2015) DBE, DME, DHE, DME\_BR, UDE-P, UDE-S

- Download the current recommended firmware:



[DBE\\_DME\\_DHE\\_UE-P\\_DME-BR\\_Main\\_T-GFSLE2AKUC\\_1033.6.zip](#)

- Unzip the file
- Rename the **T-GFSLE2AKUCRE\USB\_OU** folder to **T-GFSLE2AKUC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## For SSSP v2 (2014) DMD, DSD, DHD, UED

- Download the firmware :



[DMD\\_DSD\(40,48,55,65,75\)\\_DHD\(40,48,55\)\\_UED\\_WW\(except N.America,Korea\)Main\\_T-GFSLDWWC\\_1036.5.zip](#)

- Unzip the file
- Rename the unzipped folder to **T-GFSLDWWC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## For SSSP v2 (2014) DB22D (not DP!)

- Download the firmware :



[DBD\(22\)\\_WW\(except N.America,Korea\)Main\\_T-GFSLDDWWC\\_1035.0.zip](#)

- Unzip the file
- Rename the unzipped folder to **T-GFSLDDWWC**

- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## For SSSP v2 (2014) DB10D

- Download the firmware :



[DB10D\\_WW\(except N.America,Korea\)Main\\_T-GFSLD1DWWC\\_1008.7.zip](#)

- Unzip the file
- Rename the unzipped folder to **T-GFSLD1DWWC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

From:  
<https://documentation.zebrix.net/> - **zebrix documentation**

Permanent link:  
[https://documentation.zebrix.net/doku.php?id=en:sssp\\_usbfirmwareupdate&rev=1624521415](https://documentation.zebrix.net/doku.php?id=en:sssp_usbfirmwareupdate&rev=1624521415)

Last update: **2021/06/24 09:56**

