Samsung SSSP USB Firmware Upgrade

SSSP6 (Tizen 4) QBN/R, QMN/R, VMR QEN, OMN

- Download the current recommended firmware (**2070.3**):

http://www.zebrix.net/downloads/T-KTM2ELAKUC_USB_7070.3.zip

- **Please Note**: this firmware is referenced as **7070.3** which is the same as **2070.3** except that this special version can also be used to downgrade screen running on version superior to 2070.3
- Unzip the file
- Rename the obtained folder to **T-KTM2ELAKUC**
- Move the folder to the root of your USB drive
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

SSSP5 (Tizen) QBH, QMH, QHH, DBJ

- Download the current recommended firmware:

http://www.zebrix.net/downloads/http://www.zebrix.net/downloads/QMH_QHH_QBH_QBH-N_DBJ_Main_WW_T-KTMLAKUC_2080.2_USB.zip

- Unzip the file
- Rename the obtained folder to **T-KTMLAKUC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

SSSP4 (Tizen 2.4) PMF, PHF

- Download the current recommended firmware:

http://www.zebrix.net/downloads/PMF_PMF-BC_PHF_MLF_PHF-P_PMH_Main_WW_T-HKMLAKUC_2080.4_USB.zip

- Unzip the file
- Rename the obtained folder to **T-HKMLAKUC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

For SSSP v3 (2015) DBE, DME, DHE, DME_BR, UDE-P, UDE-S

- Download the current recommended firmware:

DBE_DME_DHE_UDE-P_DME-BR_Main_T-GFSLE2AKUC_1033.6.zip

- Unzip the file
- Rename the **T-GFSLE2AKUC*REL*USB_OU** folder to **T-GFSLE2AKUC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

For SSSP v2 (2014) DMD, DSD, DHD, UED

- Download the firmware :

DMD_DSD(40,48,55,65,75)_DHD(40,48,55)_UED_WW(except N.America,Korea)Main_T-GFSLDWWC_1036.5.zip

- Unzip the file
- Rename the unzipped folder to **T-GFSLDWWC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

For SSSP v2 (2014) DB22D (not DP!)

- Download the firmware :

DBD(22)_WW(except N.America,Korea)Main_T-GFSLDDWWC_1035.0.zip

- Unzip the file
- Rename the unzipped folder to **T-GFSLDDWWC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

For SSSP v2 (2014) DB10D

- Download the firmware :

DB10D_WW(except N.America,Korea)Main_T-GFSLD1DWWC_1008.7.zip

- Unzip the file
- Rename the unzipped folder to **T-GFSLD1DWWC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

From:
https://documentation.zebrix.net/ - **zebrix signage documentation**

Permanent link:
https://documentation.zebrix.net/doku.php?id=en:sssp_usbfirmwareupdate&rev=1624525382

Last update: **2021/06/24 11:03**