

# Samsung SSSP USB Firmware Upgrade

## SSSP6 (Tizen 4) QBN/R, QMN/R, VMR QEN, OMN

- Download the current recommended firmware (**2070.3**):



[https://downloads.zebrix.net/T-KTM2ELAKUC\\_USB\\_7070.3.zip](https://downloads.zebrix.net/T-KTM2ELAKUC_USB_7070.3.zip)

- **Please Note:** this firmware is identified as **7070.3** which is the same as **2070.3** except that this special version can also be used to downgrade screen running on version superior to **2070.3**
- Unzip the file
- Rename the obtained folder to **T-KTM2ELAKUC**
- Move the folder to the root of your USB drive
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## SSSP5 (Tizen) QBH, QMH, QHH, DBJ

- Download the current recommended firmware (**2080.2**):



[https://downloads.zebrix.net/T-KTMLAKUC\\_USB\\_7080.2.zip](https://downloads.zebrix.net/T-KTMLAKUC_USB_7080.2.zip)

- **Please Note:** this firmware is identified as **7080.2** which is the same as **2080.2** except that this special version can also be used to downgrade screen running on version superior to **2080.2**
- Unzip the file
- Rename the obtained folder to **T-KTMLAKUC**
- Move the folder to the root of your USB drive
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## SSSP4 (Tizen 2.4) PMF, PHF

- Download the current recommended firmware (**2090.2**):



[https://downloads.zebrix.net/T-HKMLAKUC\\_USB\\_7090.2.zip](https://downloads.zebrix.net/T-HKMLAKUC_USB_7090.2.zip)

- **Please Note:** this firmware is identified as **7090.2** which is the same as **2090.2** except that this special version can also be used to downgrade screen running on version superior to **2090.2**
- Unzip the file
- Rename the obtained folder to **T-HKMLAKUC**
- Move the folder to the root of your USB drive
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## For SSSP v3 (2015) DBE, DME, DHE, DME\_BR, UDE-P, UDE-S

- Download the current recommended firmware:



[DBE\\_DME\\_DHE\\_UDE-P\\_DME-BR\\_Main\\_T-GFSLE2AKUC\\_1033.6.zip](#)

- Unzip the file
- Rename the **T-GFSLE2AKUCRELUSB\_OU** folder to **T-GFSLE2AKUC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## For SSSP v2 (2014) DMD, DSD, DHD, UED

- Download the firmware :



[DMD\\_DSD\(40,48,55,65,75\)\\_DHD\(40,48,55\)\\_UED\\_WW\(except N.America,Korea\)Main\\_T-GFSLDWWC\\_1036.5.zip](#)

- Unzip the file
- Rename the unzipped folder to **T-GFSLDWWC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## For SSSP v2 (2014) DB22D (not DP!)

- Download the firmware :





[DBD\(22\)\\_WW\(except N.America,Korea\)Main\\_T-GFSLDDWWC\\_1035.0.zip](#)

- Unzip the file
- Rename the unzipped folder to **T-GFSLDDWWC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

## For SSSP v2 (2014) DB10D

- Download the firmware :



[DB10D\\_WW\(except N.America,Korea\)Main\\_T-GFSLD1DWWC\\_1008.7.zip](#)

- Unzip the file
- Rename the unzipped folder to **T-GFSLD1DWWC**
- Move the folder to the root of your USB key
- Connect the USB key to your screen
- With the remote control : Menu > Support > Software Update > Update Now
- The firmware process will take a few minutes and your screen will reboot automatically

From:

<https://documentation.zebrix.net/> - **zebrix documentation**

Permanent link:

[https://documentation.zebrix.net/doku.php?id=en:sssp\\_usbfirmwareupdate&rev=1629880175](https://documentation.zebrix.net/doku.php?id=en:sssp_usbfirmwareupdate&rev=1629880175)

Last update: **2021/08/25 10:29**

