

How to set up a video wall with Samsung screens

Step 1

Press the “HOME” button on your remote control.



Step 2

Use the navigation arrows to go to the “Video Wall” menu.



Step 3

Enable the “Video Wall” option by setting it to ON.



Step 4

Configure the following settings:

Video wall size: number of screens arranged horizontally and vertically

Screen position: position of each screen within the video wall

“Full” mode: displays the entire, uncropped picture (may not be suitable due to screen bezels)

“Natural” mode: adjusts for screen bezels to provide a more uniform overall image (the picture is automatically cropped to achieve this result)

Step 5

Assign each screen its position in the menu according to its actual physical position on the video wall, then connect the screens as follows:

Warning: connection ports may vary depending on the screen model. It is recommended to use identical screen models to build a video wall.

Example: Samsung Tizen PM series

The first screen receives the source signal (for example, from a Zebrix player). → Connect the Zebrix player to the first screen using an HDMI cable.

The second screen receives the signal from the first via a DisplayPort cable. → Connect a DisplayPort cable from the *DPOUT port of the first screen to the DPIN port of the second screen*.

Repeat this process for all remaining screens until the entire video wall is connected.

Once all screens are connected, power on the video wall and verify the configuration.

From:
<https://documentation.zebrix.net/> - **zebrix documentation**



Permanent link:
https://documentation.zebrix.net/doku.php?id=en:how_to_setup_a_video_wall

Last update: **2025/10/13 09:17**