How to upgrade SAMSUNG SSSP firmware from CMS?

- Please login to your zebrix account
- Please go the screens section
- In the list of screens please click on the "Hardware Tools" button on the line of screen you want to upgrade

🖬 📮 🚡 LAB QB13-T	Page test	Hardware Tools 🛛 🔹 💋 🗹 id % 🏛
• Go to monitor tab		

Remote	Logs	Monitor	Properties	Firmwares	Alerting
	Current Firmware		T-KTMLAKUC-2080.2		
				Q Search	
lame		Status	Description		Action
-KTMLAKUC-2130.2		Stable	SAMSUNG firmware	for SSSP5 screens	Install
-KTMLAKUC-2140.2		Experimental	SAMSUNG firmware	for SSSP5 screens	Install

• Click on the firmware button (the version on the button is the current, in the list you see available firmwares)



Please note that only compatible firmwares will be listed, depending on your screen model.

- Upgrading to the latest is the best unless there is a "BETA-VERSION-DO-NOT-USE" message.
- Your screen will download the firmware (usually takes several minutes) and will automatically upgrade and reboot.

🗌 Statut	Nom 🛃
	Écran accueil
	Écran allée centrale
	Écran boucherie
	Écran caisses
	Écran Fruits et légumes2
	OÉcran poissonerie



When the screen is downloading the firmware, it continues to work as usual (it shows content and update the content if changed). When the download of the firmware is complete, it will interrupt the playback to upgrade. This operation takes about 2 minutes then the screen will reboot and restart zebrix automatically.

From: https://documentation.zebrix.net/ - **zebrix documentation**

Permanent link: https://documentation.zebrix.net/doku.php?id=en:sssponlinefirmwareupgrade

Last update: 2023/09/05 15:08

