

Zebrix on Innes Players

How do I install zebrix on an innes player?

- Connect the player to the network using an ethernet cable
- Connect the player to a screen
- The screen should display a test card containing network information

Installation via the WebUI:

- Connect using an Internet browser with the address ipV4 or ipV6 to access the WebUI (e.g. <http://10.10.10.10/admin>)
- Enter the login and password: (admin / admin)
- Go to "Configuration" then "App"
- Select "Third Party" then "Pull Webdav"
- Enter the URL : <http://screen.zebrix.net> and enter 23:59:59 for the "heartbeat"
- Click on "Validate",
- Do not restart the player immediately
- Go to the "Maintenance" tab, then to "Test card".
- Deactivate test card
- Then restart the device using the button at top right

Installation via USB key:

- Download the configuration script:
- Format the USB key in FAT32
- Inject the script into the USB key, then into the player

Warning: The screen must display the test card before you can inject the configuration script.

The player restarts, and the Zebrix solution is launched.

Player version update :

- Enter the WebUi address on browser (corresponding to the player's ip)
- Go to "Maintenance" then "Middleware".
- Download zip file
- Unzip it, then take the file and put it in the drop box
- Restart the player

Limitations:

- PIP only works on the DMB400 model
- PIP does not work in portrait mode

DMB400 by Qeedji Redémarrer l'appareil Français

Configuration

- Administrateur
- LAN
- Sortie
- App
- Serveurs
- Licence
- Date et heure
- Régionalité
- Tâches
- Variabiles
- Commandes AV

Maintenance

Information

Configuration > App Valider Annuler

Tierce partie Relancer l'App

Lanceur d'URL

Power BI Online Viewer Désinstaller l'App

Installation de l'App: Dépôt local Push Webdav Pull Webdav

Url:

Battement de coeur:

Identifiant:

Mot de passe:

Utiliser cette URL pour le serveur de statut et le serveur d'installation des logiciels et des configurations

DMB400 by Qeedji Redémarrer l'appareil Français

Configuration

Maintenance > Mire

Mire: désactivée activée

Maintenance

- Mire
- Fichiers
- Intergiciel
- Journaux
- Préférences
- Outils

Information

DMB400
by Qeedji

Redémarrer l'appareil Français

Configuration Maintenance > Intergiciel


Maintenance

- Mire
- Fichiers
- Intergiciel**
- Journaux
- Préférences
- Outils

Information

Intergiciel : Gekkota OS - 5.11.10

Sélectionner un intergiciel pour mettre à jour votre appareil :



Déposer le fichier ici ou cliquer pour en ajouter un

From:
<https://documentation.zebrix.net/> - **zebrix documentation**

Permanent link:
https://documentation.zebrix.net/doku.php?id=en:zebrix_on_innes_players&rev=1694184578

Last update: **2023/09/08 16:49**

